











Power Connectors Size 1,5 (M40) / Contacts

Contacts	Type of Contact	Crimp Range	Part Number
	Crimp pin 2 mm, machined0,5 – 4 mm ² (AWG 20 – 12)7.015.952.001
	Crimp socket 2 mm, machined	...0,5 – 4 mm ² (AWG 20 – 12)7.015.952.002
	Crimp pin 3,6 mm, machined1,5 – 4 mm ² (AWG 16 – 12)7.015.953.601
	Crimp socket 3,6 mm, machined	..1,5 – 4 mm ² (AWG 16 – 12)7.015.953.602
	Crimp pin 3,6 mm, machined6 mm ² (AWG 10)7.015.953.611
	Crimp socket 3,6 mm, machined	...6 mm ² (AWG 10)7.015.953.612
	Crimp pin 3,6 mm, machined10 mm ² (AWG 8)7.015.953.621
	Crimp socket 3,6 mm, machined	..10 mm ² (AWG 8)7.015.953.622
	Crimp pin 3,6 mm, machined16 mm ² (AWG 6)7.015.953.631
	Crimp socket 3,6 mm, machined	..16 mm ² (AWG 6)7.015.953.632

For appropriate setting of crimp tool see page 100